

TARGET TUBE OPTION NOTES:-1. SPECIFY TUBE MATERIAL; CODE:-'R' STAINLESS STEEL 316 Ø9.45.
'S' ALUMINIUM 6063 Ø3/8" (9.2–9.8). NOTE! ONLY AVAILABLE WITH P100 OR P106 VERSIONS.

2. SPECIFY FLANGE TYPE; CODE: 'U', 'Vn', Wn' OR 'Xn' ~ SEE DETAILS BELOW.

3. SPECIFY DIMENSION n (mm), NOT APPLICABLE CODE 'U' PLAIN TUBE. -LENGTH: DISPLACEMENT + 30 (FOR 100mm DISPLACEMENT LENGTH = 130)-STANDARD PLAIN, CODE 'U' DIM 'n' -SEE NOTE 3. -MIN. 10.92 ø19.94 19.84 PENNY & GILES HLP100, CODE 'V' STAINLESS STEEL DIM 'n' ⊢SEE NOTE 3. <del>-</del> MIN. 6 ø4.4 2 PLACES-Ø24.60 -P.C.D. ø17.0 TEMPOSONICS (M4 FIXING), CODE 'W' STAINLESS STEEL 6.0 ø11.20 11.15 ø11.20 DIM 'n' SEE NOTE 3.→ MIN. 7 7.0 ø15.50-PARKER HANNIFIN, CODE 'X' STAINLESS STEEL STAINLESS STEEL CHECKED BY X ±0.4 X.X ±0.2 RDS X.XX ±0.1 DIMS mm D 12/07/05 E 16/10/06 TARGET TUBE MOUNTING NOTES, SEE DRAWING P100-12. F 24/09/08 D MINIMUM 'X' DIMENSIONS ADDED PDM G 13/11/08 H 11/12/12 E MATERIAL OPTION REMOVED. PDM TARGET TUBE AND FLANGE OPTIONS (LIPS 100/106) F MAT'L OPTION REINSTATED RAN221. PDM J 23/07/14 G X DIM FOR PH FLANGE SHOWN RAN225 K 30/11/16 RDS H 9.45 WAS 9.5 RAN396 DRAWINGS NOT TO BE CHANGED WITHOUT REFERENCE TO THE CHANGE PROCEDURE. CHANGES TO PARTS USED IN INTRINSICALLY SAFE PRODUCT MUST BE APPROVED BY THE AUTHORISED PERSON RDS SCALE DRAWING TG24-11 REV K 5mm J REDRAWN, PH FLANGE ROTATED RAN507. PDM LIMITED SHEET 1 OF 1 THIS IS AN UNCONTROLLED PRINT AND WILL NOT BE UPDATED. K NOTE 1 AMENDED ~ RAN1114. PDM



## LIPS® P116 INTERNALLY MOUNTED CYLINDER SENSOR

High-resolution position feedback for hydraulic and pneumatic cylinders

- Non-contacting inductive technology to eliminate wear
- **Fully integrated electronics**
- Travel set to customer's requirement
- Compact and easy to install
- High durability and reliability
- High accuracy and stability
- Sealing to IP67
- Frequency response of 10kHz
- Can be modified and supplied as drop in replacements for competitor products

The P116 linear sensor is designed to be fitted inside hydraulic or pneumatic cylinders allowing the external cylinder design to be unaffected.

It is an extremely durable, high-accuracy device providing position feedback for applications where service life, environmental resistance and cost are important.

It is particularly suitable for OEMs where very competitive volume pricing and unmatched overall performance make it a very attractive option. The sensor has fully integrated electronics with a variety of voltage and current outputs so no need for any external signal conditioning.

Overall performance, repeatability and stability are outstanding over a wide temperature range.

The sensor is compact and responsive along almost its entire probe length. Like all Positek® sensors each unit is supplied with the output calibrated to the exact travel required by the customer, which can be anything from 5mm up to a maximum of 600mm. It also has full EMC protection built in.

The P116 is stainless steel with an inert fluoropolymersheathed probe with a stainless steel target tube. Sealing is to IP67

The sensor is easy to install within cylinders and has a range of mechanical and electrical options.

The P116 can also be modified to match other products that are currently on the market or where the cylinder has already been machined to a specific size. they have major advantages over LVDT's, such as compact stroke to length ratio, 10kHz frequency response. In addition they have no electrically wearing parts so don't suffer the problems associated with potentiometer based devices.

Since there are no external electronics, it offers protection against accidental damage which can cause machinery downtime and increased costs.



#### **SPECIFICATION**

**Dimensions** 

**Body Diameter:** Ø27 mm 41.5 mm

Body Length: Probe Length: calibrated travel + 28 mm (nom.)

Target Tube Length calibrated travel + 30 mm

For full mechanical details see drawings P116-11
Independent Linearity \( \leq \text{0.25} \) ≤ ± 0.25% FSO @ 20°C - up to 600 mm

Temperature Coefficients < ± 0.01%/°C Gain &

< ± 0.01%FS/°C Offset > 10 kHz (-3dB)

Frequency Response Resolution

Infinite Noise < 0.02% FSO

**Environmental Temperature Limits** 

-40°C to +125°C standard -20°C to +85°C buffered Operating

-40°C to +125°C Storage

Sealing IP67 Hydraulic Pressure 350Bar

**EMC Performance** 

EN 61000-6-2, EN 61000-6-3 IEC 68-2-6: 10 g IEC 68-2-29: 40 g Vibration Shock **MTBF** 350,000 hrs 40°C Gf

**Drawing List** 

P116-11 Sensor Outline

TG24-11 Optional Target Tube Flange details Drawings; in AutoCAD® dwg or dxf format or 3D .stp are available on request.





## LIPS® P116 INTERNALLY MOUNTED CYLINDER SENSOR

### High-resolution position feedback for hydraulic and pneumatic cylinders

#### How Positek's PIPS® technology eliminates wear for longer life

Positek's PIPS® technology (Positek Inductive Position Sensor) is a major advance in displacement sensor design. PIPS®-based displacement transducers have the simplicity of a potentiometer with the life of an LVDT/RVDT.

PIPS<sup>®</sup> technology combines the best in fundamental inductive principles with advanced micro-electronic integrated circuit technology. A PIPS® sensor, based on simple inductive coils using Positek's ASIC control technology, directly measures absolute position giving a DC analogue output signal. Because there is no contact between moving electrical components, reliability is high and wear is eliminated for an exceptionally long life.

PIPS® overcomes the drawbacks of LVDT technology bulky coils, poor length-to-stroke ratio and the need for special magnetic materials. It requires no separate signal conditioning.

Our LIPS® range are linear sensors, while RIPS® are rotary units and TIPS® are for detecting tilt position. Ask us for a full technical explanation of PIPS® technology.

We also offer a range of ATEX-qualified intrinsicallysafe sensors.

#### TABLE OF OPTIONS

CALIBRATED TRAVEL: Manufactured mechanically and electrically for any measurement length from 5mm up to 600 mm

#### **ELECTRICAL INTERFACE OPTIONS**

OUTPUT SIGNAL Standard:	SUPPLY INPUT	OUTPUT LOAD
0.5-4.5V dc ratiometric Buffered:	$+5V$ dc nom. $\pm$ 0.5V.	5kΩ min.
0.5-4.5V dc 0.5-9.5V dc 4-20mA	+24V dc nom. + 9-28V. +24V dc nom. + 13-28V. +24V dc nom. + 13-28V.	5kΩ min. 5kΩ min. 300R Max.
Supply Current	10mA typical, 20mA max. plus	O/P current
CONNECTION Cable length:	Supplied with 50 cm – please s	pecify length


TARGET TUBE OPTIONS ID 7.7mm, OD 9.5mm (nom.) ID 7.1mm, OD 9.5mm (nom.) Stainless Steel (316) Aluminium (6063)


#### FLANGE OPTIONS

Penny & Giles HLP100, Temposonics (M4 fixing) and Parker Hannifin cylinders versions available. see drawing TG24-11

Sensor is supplied with oring and backup ring for sealing

required in cm.






For further information please contact: www.positek.com sales@positek.com Tel: +44(0)1242 820027 fax: +44(0)1242 820615 Positek Ltd, Andoversford Industrial Estate, Cheltenham GL54 4LB U.K.



## LIPS® SERIES P116 Internally Mounted Cylinder Sensor With External Electronics




a Displacement (mm)		Value			
Displacement in mm	e.g. 0 - 254 mm	254			
b Output					
Supply V dc $V_s$ (tolerance)	Output	Code			
+5V (4.5 - 5.5V)	0.5 - 4.5V (ratiometric with supply)	Α			
+24V nom. (13 - 28V)	0.5 - 9.5V	С			
+24V nom. (9 - 28V)	0.5 - 4.5V	G			
+24V nom. (13 - 28V)	4 - 20mA 3 wire Source	Н			
c Connections Cable*		Code			
Cable Gland	IP67	Lxx			
'Supplied with 50 cm as standard, specify required cable length specified in cm. e.g. L2000 specifies cable gland with 20 metres of cable. Nb: restricted cable pull strength.					
	es of cable. Nb: restricted cable pull strength.				
	es of cable. Nb: restricted cable pull strength.	Code			
specifies cable gland with 20 metr	es of cable. Nb: restricted cable pull strength.  OD: 9.45 mm	Code R			
specifies cable gland with 20 metr  d Target Tube					
d Target Tube Stainless Steel 316	OD: 9.45 mm OD: 3/8"	R			
d Target Tube Stainless Steel 316 Aluminium 6063	OD: 9.45 mm OD: 3/8" Target Installation details.	R			
d Target Tube Stainless Steel 316 Aluminium 6063 See P100-12 Drawing for Typical	OD: 9.45 mm OD: 3/8" Target Installation details.	R S			
d Target Tube Stainless Steel 316 Aluminium 6063 See P100-12 Drawing for Typical 1	OD: 9.45 mm OD: 3/8" Target Installation details.	R S			
d Target Tube Stainless Steel 316 Aluminium 6063 See P100-12 Drawing for Typical e Target Tube Mounti None	OD: 9.45 mm OD: 3/8" Target Installation details.  ing Flange  Please specify flange position in	R S Code			
d Target Tube Stainless Steel 316 Aluminium 6063 See P100-12 Drawing for Typical Tube Target Tube Mounti None Penny & Giles HLP100	OD: 9.45 mm OD: 3/8" Target Installation details.  ing Flange  Please specify flange position in mm. eg. W17.5 specifies a Tempo style	R S Code U Vxx			






# Installation Information LIPS® P116 INTERNALLY MOUNTED CYLINDER

Output Option	Output Description:	Supply Voltage: V <sub>s</sub> (tolerance)	Load resistance: (include leads for 4 to 20mA O/Ps)
Α	0.5 - 4.5V (ratiometric with supply)	+5V (4.5 - 5.5V)	≥ 5kΩ
С	0.5 - 9.5V	+24V nom. (13 - 28V)	≥ 5kΩ
G	0.5 - 4.5V	+24V nom. (9 - 28V)	≥ 5kΩ
Н	4 - 20mA 3 wire Source	+24V nom. (13 - 28V)	≈ 0 - 300Ω max. ~ 1.2 to 6V across 300Ω



Mechanical Mounting: The sensor is intended for internal mounting in hydraulic or pneumatic cylinders. Retain with an M6 grub screw, see drawing P116-11 for details. Install the target tube using the flange provided or adhere directly into the piston rod, the end of the target tube can be proud or flush with the piston end face as required.

**Output Characteristic:** Target position at start of normal travel is 21 mm from sensor body. The output increases as the target is moved away from the sensor body, the calibrated stroke is between 5 mm and 800 mm.



#### **Incorrect Connection Protection levels:-**

A Not protected – the sensor is not protected against either reverse polarity or over-voltage. The risk of damage should be minimal where the supply current is limited to less than 50mA.

C & G Supply leads diode protected. Output must not be taken outside 0 to 12V.

Supply and output lead diode protected. Do take output negative of 0 volts.

